

ASe Processor Settings

November 13, 2001



AS300e biamp

OUTPUT	Name	Low	Mid/Hi
GAIN	(dB)	4.0	0.0
DELAY	(ms)	0.00	0.08
POLARITY		Positive	Positive
HPF	Freq (Hz)	40.5	445
	Slope (dB)	24	24
	Shape	Butterworth	Linkwitz-Riley
LPF	Freq (Hz)	385	thru
	Slope (dB)	24	
	Shape	Butterworth	
PEQ1	Freq (Hz)	50	1542
	Level (dB)	6.0	-4.0
	Type	Parametric	Parametric
	Q	2.00	1.12
	(Bandwidth)	0.50	0.89
PEQ2	Freq (Hz)	216	971
	Level (dB)	-2.5	-1.5
	Type	Parametric	Parametric
	Q	5.34	3.56
	(Bandwidth)	0.19	0.28
PEQ3	Freq (Hz)	167	612
	Level (dB)	3.5	1.0
	Type	Parametric	Parametric
	Q	5.34	2.00
	(Bandwidth)	0.19	0.50
PEQ4	Freq (Hz)	545	6169
	Level (dB)	-7.0	-2.0
	Type	Parametric	Parametric
	Q	3.17	3.56
	(Bandwidth)	0.33	0.28
PEQ5	Freq (Hz)		5040
	Level (dB)		2.0
	Type		Parametric
	Q		4.24
	(Bandwidth)		0.24

NOTE: To use system with sub, high pass LF @ 80 Hz (24 dB Butterworth) & do not use PEQ 1.