

**QX594 Bi-Amp**

| Output   | Name       |
|----------|------------|
| GAIN     | (dB)       |
| DELAY    | (ms)       |
| POLARITY |            |
| HPF      | Freq (Hz)  |
|          | Slope (dB) |
|          | Shape      |
| LPF      | Freq (Hz)  |
|          | Slope (dB) |
|          | Shape      |
| PEQ1     | Freq (Hz)  |
|          | Level (dB) |
|          | Type       |
|          | Q          |
| PEQ2     | Freq (Hz)  |
|          | Level (dB) |
|          | Type       |
|          | Q          |
| PEQ3     | Freq (Hz)  |
|          | Level (dB) |
|          | Type       |
|          | Q          |
| PEQ4     | Freq (Hz)  |
|          | Level (dB) |
|          | Type       |
|          | Q          |
| PEQ5     | Freq (Hz)  |
|          | Level (dB) |
|          | Type       |
|          | Q          |
| PEQ6     | Freq (Hz)  |
|          | Level (dB) |
|          | Type       |
|          | Q          |
| PEQ7     | Freq (Hz)  |
|          | Level (dB) |
|          | Type       |
|          | Q          |
| PEQ8     | Freq (Hz)  |
|          | Level (dB) |
|          | Type       |
|          | Q          |

| LF          | MF/HF       |
|-------------|-------------|
| 3.9         | -3.5        |
| 0.55        | 0           |
| Positive    | Negative    |
| 60          | 595         |
| 12          | 24          |
| Butterworth | Butterworth |
| 447         | 18836       |
| 24          | 24          |
| Butterworth | Butterworth |
| 334         | 4731        |
| -12         | 6           |
| Parametric  | Parametric  |
| 1.33        | 3.75        |
| 75          | 750         |
| 6.5         | -4          |
| Parametric  | Parametric  |
| 1.68        | 2.11        |
| 112         | 1122        |
| -0.5        | -4          |
| Parametric  | Parametric  |
| 2.24        | 4.47        |
| 447         | 1540        |
| 8.5         | -4          |
| Parametric  | Parametric  |
| 4.21        | 4.47        |
|             | 2175        |
|             | -2.5        |
|             | Parametric  |
|             | 7.5         |
|             | 2985        |
|             | -8.5        |
|             | Parametric  |
|             | 5.31        |
|             | 531         |
|             | 4           |
|             | Parametric  |
|             | 1.67        |
|             | 12589       |
|             | 5.5         |
|             | Parametric  |
|             | 1.78        |

Output gains assume all amplifiers have the same voltage gain