UXR Touring Racks



UXR custom-built amplifier racks are available in two models; UXR316 or UXR216. Each UXR amp rack comes with custom power, input, and output panels and is equipped with rigging making it possible to suspend one or multiple UXR amp racks.

Side rigging allows multiple side by side UXR amp racks to be secured together keeping the stage area clean and organized. Front mounted cabling allows the racks to be located against walls and stages, reducing the system's stage footprint and ensuring you always have fast physical and visual access to patching.

The UXR input panel provides all amplifier analog inputs and loops at the front of the amp rack. A high-quality Dante certified switch supports Dante signal routing inside the rack, between multiple UXR amplifier racks, and front of house. In situations when redundant digital networks are required a second switch can be added. The outputs of each amp are available on NL4 and NL8 connectors enabling exceptional output wiring flexibility.

TECHNICAL SPECIFICATIONS

RACK CONTENTS	
Amplification	2 or 3 UXA4416D 4x4000W
Network	1 or 2 Luminex GigaCore 10 switches
Connectivity	1 UXR Power Distro 1 UXR Audio Panel
Misc	3 or 6 1GB Cat 5e 4 AES jumper cables
POWER DISTRIBUTION	
AC Input / Link (US)	30A - NEMA L21-30 (3P+N+G) male / female outlet
AC Input /Link (EU)	32A - IEC 60309 (3P+N+E) male / female outlet
AC Presence	3x LEDs
AC Auxiliary output (US)	NEMA 5-15 (Front / Rear)
AC Auxiliary output (EU)	Universal (US UK EU) 3-prong (Front / Rear)
Protection	15A resetable (US) or 16A breaker (EU)
AC Output for UXA	3 x 32A PowerCON, 208V (US) or 230V (EU)
AC output for network	2 x 16A True1 PowerCON
CABLES	
Analog	6 AES compatible XLR, 4ft tail
Network	3 or 6 1GB Cat 5e, 2 ft tail
AES/EBU	4 AES/EBU jumper, 1ft
RIGGING & TRANSPORT	
Rigging Hardware	Integrated 2-point rigging
Flybar	2042596 Flybar Amp Distro Rack [FB Rack]
Caster Pallet	2072324 UXR Caster Pallet
Gang Bracket	2072493-90 UXR Gang Bracket Kit



UXR FRONT PANEL VIEW



