

QX566 Bi-Amp

Output	Name
GAIN	(dB)
DELAY	(ms)
POLARITY	
HPF	Freq (Hz)
	Slope (dB)
	Shape
LPF	Freq (Hz)
	Slope (dB)
	Shape
PEQ1	Freq (Hz)
	Level (dB)
	Type
	Q
PEQ2	Freq (Hz)
	Level (dB)
	Type
	Q
PEQ3	Freq (Hz)
	Level (dB)
	Type
	Q
PEQ4	Freq (Hz)
	Level (dB)
	Type
	Q
PEQ5	Freq (Hz)
	Level (dB)
	Type
	Q
PEQ6	Freq (Hz)
	Level (dB)
	Type
	Q
PEQ7	Freq (Hz)
	Level (dB)
	Type
	Q

LF	MF/HF
3.6	-5.5
0.45	0
Positive	Negative
60	595
12	24
Butterworth	Butterworth
447	
24	
Butterworth	
281	944
-10.5	-6
Parametric	Parametric
1.18	1.33
75	487
7	5
Parametric	Parametric
1.88	1.58
163	2113
0.5	-3.5
Parametric	Parametric
2.37	3.76
410	2985
5	-6.5
Parametric	Parametric
2.37	5.96
	4870
	7
	Parametric
	2.11
	13725
	7
	Parametric
	2.37
	1540
	-3.5
	Parametric
	2.66

Output gains assume all amplifiers have the same voltage gain